

PRAMAC S 7200

Item code: PD612MHB001,PD612MHB002



Características Principales

Power (LTP) : 7.20 kW
Voltage : 120, 240 V
Frequency : 60 Hz
Engine manufacturer : Honda
Fuel type : Gasoline
Starting system : Recoil, Electric

Serie S

La serie S se diseñó pensando en el profesional. Tiene todas las características que pueden necesitarse para cumplir con las demandas de las aplicaciones más exigentes.

Especificaciones Técnicas

Single phase

Power (LTP)	7.20 kW
Power (COP)	6.10 kW

Power specifications

Voltage	120, 240 V
Amps at 120V (LTP)	60 A
Amps at 120V (COP)	50.8 A
Amps at 240V (LTP)	30 A
Amps at 240V (COP)	25.4 A
Frequency	60 Hz
Power factor	1 cosPhi

Engine specifications

Engine manufacturer	Honda
Model	GX 390
Fuel type	Gasoline
Displacement	389 cc
Cycle	4
Power	8.2 kW
	11 HP
Aspiration	Natural

Cooling system	Air
Starting system	Recoil, Electric

Consumption

Fuel consumption at 100% of load	0,87 gal/h
Fuel tank capacity	8,00 gal
Running time at 100% of load	9,2 h

Noise emission

Noise pressure level at 7 m	74 dBA
-----------------------------	--------

Dimensions and weight

Length	31,38 in
Width	22,24 in
Height	26,26 in
Weight (dry)	199,08 lb

www.proyeg.com

servicio@proyeg.com

PBX (502) 2485 4300.